



## Main

Product or component type	Load Center
Range of product	Homeline
Load center type	Main breaker
Line Rated Current	150 A
Number of spaces	8
Number of circuits	16
NEMA degree of protection	NEMA 3R outdoor
Cover type	Surface cover
Electrical connection	Feed-thru lugs
Provided equipment	Circuit breaker (1) 2P 150 A 120/240 V AC main supply ready assembled Grounding bar (1) ready assembled

## Complementary

Short-circuit current	22 kA
Number of tandem circuit breakers	8
Phase	1 phase
System Voltage	120/240 V AC
AWG gauge	AWG 4...250 kcmil (copper or aluminium)
Wiring configuration	3-wire
Cover finish	Gray baked enamel
Material	Tin plated aluminium busbar
Enclosure material	Welded galvanized steel
Surface finish	Baked enamel grey
Box number	6R
Height	29.84 in (758 mm)
Width	14.76 in (375 mm)
Depth	4.53 in (115 mm)

## Environment

product certifications	UL E-6294
------------------------	-----------

## Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 1414 - Schneider Electric declaration of conformity	Compliant - since 1414 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.