



### Main

|                           |                      |
|---------------------------|----------------------|
| Product or component type | Full voltage starter |
| Range of product          | Instakits            |
| Starter Type              | Non reversing        |

### Complementary

|                        |  |
|------------------------|--|
| System Voltage         | 120 V AC at 50/60 Hz   |
| Current Rating         | 40 A   |
| Horsepower Rating      | 5 hp at 240 V AC for 1 phase motors<br>10 hp at 208 V AC for 3 phases motors<br>10 hp at 230 V AC for 3 phases motors<br>3 hp at 120 V AC for 1 phase motors<br>30 hp at 460 V AC for 3 phases motors<br>30 hp at 575 V AC for 3 phases motors |
| Maximum Voltage Rating | 600 V AC   |
| Auxiliary Contacts     | 1 NO + 1 NC  |
| Protection type        | Switch-disconnector fuse   |
| Location of connection | Line   |

### Environment

|                        |                  |
|------------------------|------------------|
| Product certifications | CSA<br>IEC<br>UL |
| Enclosure Type         | NEMA 1 steel     |

### Offer Sustainability

|                        |   |
|------------------------|---|
| RoHS (date code: YYWW) | Compliant - since 1444 - Schneider Electric declaration of conformity<br><a href="#">Schneider Electric declaration of conformity</a> |
|------------------------|---|

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications.