



## BFR H1-1/2"



L = 10 FT / 3 m




To assemble trays, it is necessary to use a bolt-washer set for each of the cable tray's side, with reference number 2/4364 in EZ.

	Width		SWL	Weight	FINISH
	inch	mm	(Lbs/ft)d=5ft	LBS/EA	REF. EZ
BFR 4" x 1-1/2"	4"	100	15	3.37	2/3616
BFR 6" x 1-1/2"	6"	150	15	4.56	2/3617
BFR 8" x 1-1/2"	8"	200	15	5.49	2/3618
BFR 12" x 1-1/2"	12"	300	19	7.80	2/3619

## BF2R H2"



L = 10 FT / 3 m




Self splicing system. For mounting the cable trays there is no need to use more items.

	Width		SWL	Centerpiece	UTP CAT 6	Weight	FINISH		
	inch	mm	(Lbs/ft)d=5ft	units	(0.24')		LBS/EA	REF. EZ	REF. Black
BF2R 2" x 2"	2"	60	8	0	-	4.93	2/7389	U/0299	U/0600
BF2R 4" x 2"	4"	100	19	0	74	5.22	2/7248	U/0300	U/0601
BF2R 6" x 2"	6"	150	21	0	124	5.56	2/7249	U/0301	U/0602
BF2R 8" x 2"	8"	200	32	0	171	7.21	2/7250	U/0302	U/0603
BF2R 12" x 2"	12"	300	38	1	267	10.45	2/7251	U/0303	U/0604
BF2R 16" x 2"	16"	400	37	1	364	13.29	2/7394	U/0304	U/0605
BF2R 18" x 2"	18"	450	43	2	410	16.53	2/9989	U/0305	U/0606
BF2R 20" x 2"	20"	500	43	2	459	17.66	2/7395	U/0306	U/0607
BF2R 24" x 2"	24"	600	43	2	555	20.70	2/7396	U/0307	U/0608

## BF2R H4"



L = 10 FT / 3 m



Self splicing system. For mounting the cable trays there is no need to use more items.

	Width		SWL	Centerpiece	UTP CAT 6	Weight	FINISH		
	inch	mm	(Lbs/ft)d=5ft	units	(0.24')		LBS/EA	REF. EZ	REF. Black
BF2R 4" x 4"	4"	100	32	0	139	7.21	2/7914	U/0308	U/0609
BF2R 6" x 4"	6"	150	32	0	229	7.54	2/7915	U/0309	U/0610
BF2R 8" x 4"	8"	200	48	0	318	10.52	2/7397	U/0310	U/0611
BF2R 12" x 4"	12"	300	51	1	498	13.29	2/7398	U/0311	U/0612
BF2R 16" x 4"	16"	400	75	1	679	17.92	2/7399	U/0312	U/0613
BF2R 18" x 4"	18"	450	73	2	768	19.31	2/9990	U/0313	U/0614
BF2R 20" x 4"	20"	500	72	2	859	20.64	2/7400	U/0314	U/0615
BF2R 24" x 4"	24"	600	79	2	1038	23.35	2/7401	U/0315	U/0616

SWL = Safety Working Load