



### Main

Range of product	9080GCB
Product or component type	Circuit Protector
Trip unit technology	Thermal-magnetic
Electrical connection	Box lugs

### Complementary

Protection type	Overcurrent
Contact operation	Trip-free
Device application	Industrial application
Line Rated Current	10 A
Poles description	1P
System Voltage	125 V AC 65 V DC
AWG gauge	AWG 16...AWG 10 (copper)
Wire stripping length	0.5 in
Tightening torque	7 lbf.in control circuit cage type connector
Wiring device additional information	Factory wiring only
Ambient air temperature for operation	-22...140 °F
Temperature for tripping	70 °F
Mounting support	35 mm DIN rail 9080GH track
Height	3.45 in
Width	3.15 in
Depth	0.5 in

### Environment

product certifications	CE UL recognized E233026 CCN QVNU2 CSA file 025490 class 3211 07
standards	UL 1077 DIN 57470 CSA C22.2 No 235

### Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0934 - Schneider Electric declaration of conformity	Compliant - since 0934 - Schneider Electric declaration of conformity
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

### Contractual warranty

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

