



Product availability: Stock - Normally stocked in distribution facility

Main

| | |
|--------------------------------|-----------------------------------------------------|
| Commercial Status | Commercialised |
| Product or component type | Molded Case Circuit Breaker |
| Range of product | PowerPact H |
| [In] rated current | 60 A |
| Poles description | 3P |
| Breaking capacity | 25 kA 600 V AC 65 kA 480 V AC 100 kA 240 V AC |
| [Ue] rated operational voltage | 600 V AC |
| Trip unit technology | Thermal-magnetic |
| Product certifications | CSA IEC UL listed |
| Mounting mode | Plug-in |
| Breaking capacity code | J |
| Electrical connection | Lugs load I-Line connection line |
| AWG gauge | 14...3/0 AWG aluminium/copper |
| Phase connection | ABC |
| Magnetic hold current | 800 A |
| Magnetic tripping current | 1450 A |

Ordering and shipping details

| | |
|-----------------------|---------------------------------------------------|
| Category | 01117 - HG, HJ, JG, JJ I-LINE BREAKER/SWITC |
| Discount Schedule | DE2 |
| GTIN | 00785901600961 |
| Nbr. of units in pkg. | 1 |
| Package weight(Lbs) | 5.82 |
| Product availability | Stock - Normally stocked in distribution facility |
| Returnability | Y |
| Country of origin | US |

Offer Sustainability

| | |
|--------------------------|---------------------------------------------------------------------------------------|
| Sustainable offer status | Not Green Premium product |
| RoHS | Compliant - since 0832 - Schneider Electric declaration of conformity |

Contractual warranty

| | |
|--------|-----------|
| Period | 18 months |
|--------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.