Product data sheet Characteristics

2510FO2

FHP Manual Starter - Open - 2P - Toggle Operated - No Indicator - 277VAC





Main

*********		ā
Product	Single Unit Manual Starter	
Туре	F	-
Overload Relay Type	Melting alloy	

Complementary

Cable entry Without Horsepower Rating 1 hp at 115 V AC 1 hp at 277 V AC 0.75 hp at 115 V DC 0.75 hp at 230 V DC 2 hp at 230 V AC System Voltage 277 V AC 230 V DC Number of Poles 2P Control Unit Toggle switch	
1 hp at 277 V AC 0.75 hp at 115 V DC 0.75 hp at 230 V DC 2 hp at 230 V AC System Voltage 277 V AC 230 V DC Number of Poles 2P	
230 V DC Number of Poles 2P	determining suitability
Control Unit Toggle switch	— <u></u>
	c
Phase 1 phase	
Pilot Light No indicator	
Reset Manual	— albetitite
Motor starter type Non reversing	ď
Electrical connection Screw clamp terminals	a
Wire Gauge AWG 14AWG 12 (copper)	
Height 4.13 in	
Width 1.69 in	<u>.</u>
Depth 2.22 in	——mentation

Environment

		· · · · · · · · · · · · · · · · · · ·
Product certifications	CSA LR25490 class 3211 05	<u> </u>
	UL recognized E42243 CCN NLRV2	<u></u>

NEMA Enclosure Rating	Not rated (open device)	
Offer Sustainability		
RoHS (date code: YYWW)	Will not be compliant	
	Will not be compliant	
Contractual warranty		
Warranty period	18 months	